

# TENS, EMS, IFT and Russian Stimulator

# **BLD Stim<sup>3</sup>**



# **Features**

- True Sinewave IFT with four pole application
- Vector effect ( 100% modulation of amplitude)
- Independent 4 channels
- Carrier Frequency 5000 Hz
- LCD Digital display
- Battery & Adapter Operated

#### **Profession Interferential for Home Visit**

The BLD Stim3 is one of the most popular and successful devices for physical therapy. It provides all therapies in a single hand held device for physical therapist and home care professionals. The BLD Stim3 provides two/four channels, delivering four treatments from a single unit.

### **Technical Specification**

Output	-	Two (Four Channel and 8 Electrodes)
Waveform	-	Sine Wave and Symm. Biphasic Sq. Wave
Modes	-	IFT: Low, High, Wide & Fixed
	-	TENS: Conv. Burst & Modulation
	-	EMS: Conv. and Russian
IFT Carrier Freq.	-	5000 Hz
Sweep	-	1 - 10 Hz (Low)   80 - 150 Hz (High)
	-	1 - 250 Hz. (Wide)   10 - 200 Hz (Fixed)
EMS/TENS Freq.	-	1 - 150 Hz
Russian Freq.	-	2500 Hz. (Carrier) / 50 Hz. (Beat)
Pulse Width	-	TENS : 50 - 250 μS
	-	EMS : 200 - 450 μS
Ramp Up/ Down	-	1 - 10 Seconds
Cont. / Relax. Time	· -	1 - 30 Seconds
Output Voltage	-	50 Volts peak to peak
Treatment Time	-	1 - 60 Minutes
Power	-	Four 1.2 Volt AA Size Batteries
		5.5 Volt Adaptor



## Johari Digital Healthcare Ltd.

G-582-584, E.P.I.P. Boranada, Jodhpur 342008 Raj. India, TEL: 1800-102-8684 Email: info@joharidigital.com www.joharidigital.com

All rights reserved. Although every care has been taken to provide accurate and up-to-date information, no responsibility can be accepted for any mistakes or misprints contained in this catalogue. The products and their specifications, as shown in this catalogue, may differ according to the country where they are sold.